

Range: **CYCLIC AGM**Type name: **TBC12-100**

Barcode: **8436594880575**







PE	RFORMANCES*	CONFIGURATION				
Voltage:	12 V	Size:	330x173x212 mm (G31)			
Capacity:	107 Ah (20h)	Polarity:	1			
Cap. 5/10/100h:	88/100/112 Ah	Terminal:	M (M8 thread)			
Energy at 100h:	1,35 kWh	Holddown:	-			
Cycles at 50%:	700	Ventilation	Valve regulated (VRLA)			
Max. current:	1200 A (5seg)	Maintenance:	Not required (MF)			
Int. Resistance:	5 mΩ					
Self-Discharge:	15 months					
	(from the date of production, at 25°C)					

^{*}According to standards IEC 60254/60896

INTE	RNAL CONSTRUCTION	COMPONENTS			
Technology:	Manufacturer-sealed AGM	Container:	ABS/light grey		
		Lid:	ABS/dark grey		
Alloy:	Calcium	Plugs:	Termal sealing, ABS/dark grey		
Separator:	AGM (glass mat)	Handles:	On lid, PP/dark grey		
Total Weight:	31 kg				
Origin:	Asia				

RECOMMENDATIONS						
Storage:	Check voltage every 8 months.					
Recharge:	Use automatic chargers with constant voltage and AGM setup.					
Installation:	Use the apropriate cable section and length. Keep connections tight.					

CEMA Baterías is the exclusive importer for Europe of DECK Battery products







TABLES & CHARTS


CYCLIC AGM


TBC12-100


		Т	BC12-1	100 Co	nstant	Curre	nt Disc	charge	(Amp	eres) a	t 25 °C			
F.V/Time	10min	15min	20m in	30m in	45min	1h	2h	3h	4h	5h	6h	8h	10h	20h
1.85V/cell	146.4	123.2	107.7	77.5	61.5	49.9	31.0	24.2	19.6	15.9	13.9	11.3	9.4	5.31
1.80V/cell	187.1	148.9	127.3	91.4	71.6	55.9	33.9	26.0	20.9	17.1	14.9	12.0	10.0	5.36
1.75V/cell	205.6	162.6	136.9	94.9	74.3	58.5	35.1	26.5	21.4	17.5	15.3	12.2	10.1	5.41
1.70V/cell	224.1	173.6	143.9	98.8	77.2	60.4	36.5	27.2	22.0	18.0	15.6	12.4	10.2	5.51
1.65V/cell	241.8	184.6	152.8	104.2	79.2	62.4	37.5	28.4	22.7	18.5	16.0	12.6	10.4	5.58
1.60V/cell	262.5	197.4	162.8	110.0	82.5	64.6	38.8	29.3	23.4	19.1	16.3	12.7	10.5	5.61
		ū	BC12-	100 Co	nstant	Powe	r Discl	narge (Watts	cell) a	t 25 °C			
F.V/Time	10min	15min	20m in	30m in	45min	1h	2h	3h	4h	5h	6h	8h	10h	20h
1.85V/cell	273.2	232.3	205.2	148.8	119.0	96.9	60.4	47.2	38.4	31.3	27.4	22.4	18.7	10.6
1.80V/cell	344.4	276.5	238.8	173.5	137.3	107.9	65.6	50.6	40.8	33.5	29.3	23.7	19.8	10.7
1.75V/cell	373.8	299.1	254.8	179.3	141.8	112.5	67.8	51.4	41.6	34.3	30.1	24.1	20.0	10.8
1.70V/cell	401.7	316.9	266.3	185.8	147.0	115.7	70.3	52.7	42.6	35.1	30.7	24.5	20.2	11.0
1.65V/cell	430.4	334.8	281.5	195.2	150.2	119.2	72.1	54.8	44.0	36.0	31.3	24.8	20.6	11.1
	459.4	353.8	296.8	204.0	155.1	122.5	74.1	56.2	45.1	37.0	31.9	25.0	20.8	11.2













No supplementary charge required

(Carry out supplementary charge before use if 100% capacity is required.)

Supplementary charge required before use. Optional charging way as below:

1. Charged for above 3 days at limited current 0.25CA and constant volatge 2.25V/cell.

2. Charged for above 20hours at limited current 0.25CA and constant volatge 2.45V/cell.

3. Charged for 8~10hours at limted current 0.05CA.

Supplementary charge may often fail to recover the capacity
The battery should never be left standing till this is reached.

